

MOTION
CONTROL PRODUCTS

Innovative products
for automation
industry

MACK
uni **NANO**

MKUN

SERVODRIVE

USB

EtherCAT

CANopen

RS 485 RTU

12-140 VDC	40 ARMS	2500 W
---------------	------------	-----------

P.N. : D.S. / 13.07.17 / MKUN / P05

DRIVE MODEL	MKUN 48				MKUN 60		MKUN 110		MKUN 140	
SIZE	1	5	8	10	25	40**	15	35	8	25
Rated Current (Arms)	1	5	8*	10*	25**	40**	15**	35**	8**	25**
Peak Current x 3 sec (Arms)	2	10	16	20	50	80	30	70	16	50
Power Supply	12 - 48 VDC (9 VDC min. – 65 VDC max.)				12 - 60 VDC (9 VDC min. – 82 VDC max.)		12 - 110 VDC (9 VDC min. – 130 VDC max.)		20 - 140 VDC (9 VDC min. – 182 VDC max.)	
Backup Logic Supply	12 - 24 VDC (9 VDC min. – 30 VDC max.)									
WEIGHT	75 g (CASE A)					110g (CASE B)				

NOTE * : Rated current refers to drive mounted on cabinet metal plate
 ** : Rated current refers to drive mounted on aluminium plate or heat-sink (85°C max). Contact us for details.

STANDARD FEATURES

- ◆ Driving motor range up to 2500W
 - ◆ Sinusoidal waveform current
 - ◆ **BL** Brushless and **DC** Brushed Motor Control
 - ◆ **EI** Incremental Encoder feedback for **DC** brushed motors, **SM** stepper motors
 - ◆ **EIS** Incremental Serial Encoder feedback for **BL** brushless motors
 - ◆ **EC** Commutation Encoder feedback for **BL** brushless motors
 - ◆ **HS** Hall feedback for **BL** brushless motors
 - ◆ **RA** Armature feedback for **DC** brushed motors
 - ◆ **SL** Sensorless feedback for **BL** brushless, **SM** stepper motors
 - ◆ **CD** Clock and Direction Command
 - ◆ **RD** Differential analogue ref. velocity command ±10V (12 bit)
 - ◆ **CB** Can BUS, **MB** ModBus-RTU, RS 485 Interface
 - ◆ Two tone led drive status signal
 - ◆ Over / Under voltage, over temperature, overcurrent and I²t monitoring
 - ◆ **Speeder-One**® software interface (Windows based)
 - ◆ **USB** access for setting and monitoring
 - ◆ 4 INPUT / 2 OUTPUT programmable
 - ◆ Operating frequency 8KHz (default) / 16KHz* / 24KHz*
 - ◆ Current loop update rate 8KHz ◆ Position & velocity update rate 4KHZ
-
- ◆ Ambient temp.¹: - operating at rated data: 0 - 40°C (no derating)
 - rated & pk current derating: 40 - 55°C max (2.5% / °C)
 - storage -20 - 55°C
 - ◆ Ambient Humidity¹: - operating & storage . 85% RH max
 - ◆ Altitude (a.m.s.l.): - operating & storage . 1000m
 - rated & pk current derating: up to 2500m (1.5% / 100m)
 - ◆ Protection rating: IP20 ◆ Storage time. 1 year²

OPTIONS

- ◆ **S** Stepper Motor Control (for case A only)
- ◆ **EC** EtherCAT
- ◆ **STO** Safe Torque Off
- ◆ **Dumping Circuit**

APPLICATIONS

- ◆ Printing Machines
- ◆ Textile Machines
- ◆ Coding Machines
- ◆ Conveyors
- ◆ Machine Tools
- ◆ AGV Battery operated Machines
- ◆ Upgrade replacement for stepper system
- ◆ Packaging Machines
- ◆ Sewing Machines
- ◆ Jewellery Machines
- ◆ Actuators
- ◆ Door operators
- ◆ Antenna positioners
- ◆ CNC axis control

NOTES: * 16KHz / 24KHz with derating of drive performances. Contact us for details.

¹ Free from condensation

² After one year storage the electrolytic capacitors must be reformed. Contact us for details.



80 77

22,6

Ø 4

M BRUSHLESS

1	U
2	V MOTOR
3	W
4	N.C.

M BRUSHED

1	N.C.
2	+M MOTOR
3	-M
4	N.C.

M STEPPER

1	A
2	B
3	A- MOTOR
4	B-

PS SUPPLY

1	+ AT
2	- AT
3	+ Bkup
4	- Bkup
5	+ RR
6	- RR

CM CONTROL

1/2/3/4	D. IN 1/2/3/4
5/10	AGND
6	An / D.OUT 1
7	D.OUT 2
8/9	An.IN 1 +/-
11/12	D.IN HS 5 +/-
13/14	D.IN HS 6 +/-

FM FEEDBACK

1	+ Ch. A / Data + / SE +
2	- Ch. A / Data - / SE -
3/4	Ch. B +/-
5	+ Ch. Z / (Zs) / Clock +
6	- Ch. Z / (Zs) / Clock -
7/8/9	Hall U / V / W
10	+ Tacho
11	AGND (-Tacho)
12	+5Vs

STO SAFE

1/2	STO.IN 1 / 2
3/4	AGND
5/6	STO.OUT 1 / 2
7/8	N.C.
9	N.C.
10	N.C.

ETHERCAT uniNANO

Hw MKUN48/8-B-X-EC-00-Sxxx
Sw X000/X000
PN 00000000 SN 00000000

SUPPLY PS MOTOR M FEEDBK
1 2 3 5 1 3 1 11
2 4 6 2 4 2 FM 12

42

LED

- ☀️ READY (flash)
- RUN
- ☀️ P_t (flash)
- ALARM

CANopen
RS 485 RTU
RJ1 = RJ2

1 Can H
2 Can L
3 Can Gnd
4 RS485 A
5 RS485 B
6 N.C.
7 PGND
8 Bypass

EtherCAT
RJ1=INPUT
RJ2=OUTPUT

1 TX +
2 TX -
3 RX +
4 Reserved
5 Reserved
6 RX -
7 Reserved
8 Reserved

CASE A

80 77

45

Ø 3.3

Ø 4

CM CONTROL

1/2/3/4	D. IN 1/2/3/4
5/10	AGND
6	An / D.OUT 1
7	D.OUT 2
8/9	An.IN 1 +/-
11/12	D.IN HS 5 +/-
13/14	D.IN HS 6 +/-

FM FEEDBACK

1	+ Ch. A / Data + / SE +
2	- Ch. A / Data - / SE -
3/4	Ch. B +/-
5	+ Ch. Z / (Zs) / Clock +
6	- Ch. Z / (Zs) / Clock -
7/8/9	Hall U / V / W
10	+ Tacho
11	AGND (-Tacho)
12	+5Vs

STO SAFE

1/2	STO.IN 1 / 2
3/4	AGND
5/6	STO.OUT 1 / 2
7/8	N.C.
9	+Bkup
10	Bkup

Hw MKN60/25-B-X-CB-Sxxx
Sw X000/X000
PN 00000000 SN 00000000

PE ⊕ PE ⊕

39

16

23,37

+AT -AT U V W

LED

- ☀️ READY (flash)
- RUN
- ☀️ P_t (flash)
- ALARM

CANopen
RS 485 RTU
RJ1 = RJ2

1 Can H
2 Can L
3 Can Gnd
4 RS485 A
5 RS485 B
6 N.C.
7 PGND
8 Bypass

EtherCAT
RJ1=INPUT
RJ2=OUTPUT

1 TX +
2 TX -
3 RX +
4 Reserved
5 Reserved
6 RX -
7 Reserved
8 Reserved

CASE B

CM CONTROL	FM FEEDBACK
1/2/3/4	D. IN 1/2/3/4
5/10	AGND
6	An / D.OUT 1
7	D.OUT 2
8/9	An.IN 1 +/-
11/12	D.IN HS 5 +/-
13/14	D.IN HS 6 +/-
1	+ Ch. A / Data + / SE +
2	- Ch. A / Data - / SE -
3	Ch. B +
4	Ch. B -
5	+ Ch. Z / (Zs) / Clock +
6	- Ch. Z / (Zs) / Clock -
7	Hall U
8	Hall V
9	Hall W
10	+ Tacho
11	AGND (-Tacho)
12	+5Vs

POWER SUPPLY / MOTOR

BRUSHED	BRUSHLESS
+AT	+AT
-AT	-AT
PE	PE
U	U
V	V
W	W
PE	PE

POWER SUPPLY

MOTOR

MACK® uni NANO

MKUN48 / 8 - B - X - CB - 0 0 - Sxxx

HARDWARE CODE

SOFTWARE CODE

DRIVE LINE

SIZE

MOTOR TYPE:
B = Standard:
BL Brushless
DC Brushed
S = Optional: (for case A only)
SM Stepper
BL Brushless
DC Brushed

FEEDBACK:
X = Standard

CONTROL MODE:
CB = Can BUS (std)
RS 485 MODBUS-RTU
EC = EtherCAT (opt)

STO (Safe torque Off):
0 = w/out (std), 1 = with (opt)

DUMPING CIRCUIT:
0 = w/out (std)
1 = with (opt)

SPEC. NUMBER (opt)

FIRMWARE VERSION

CONFIG FILE